


# Copper Grip Washers



Clearance Hole Metric - BA mm	Diameter ins/mm	Thickness ins/mm
M4 4BA - 4.0	0.285/7.25	0.032/0.80
M4 4BA - 4.0	0.362/9.20	0.032/0.80
M5 2BA - 5.0	0.362/9.20	0.032/0.80
M4.8 3/16 - 5.0	0.446/11.30	0.032/0.80
M5 3/16 - 4.7	0.495/12.58	0.036/0.90
M6 7/32 - 5.5	0.618/15.70	0.040/1.00
M6 1/4 - 6.3	0.687/17.45	0.048/1.20
M8 5/16 - 8.0	0.742/18.85	0.056/1.40
M8 5/16 - 8.0	0.894/22.71	0.064/1.60
M10 3/8 - 9.5	0.915/23.24	0.072/1.80
M11 7/16 - 10.1	1.00/25.40	0.080/2.00
M10 3/8 - 9.5	1.145/29.00	0.092/2.33
M13 1/2 - 12.7	1.145/29.00	0.09/2.33

Used for electrical terminations where a cable end is clamped and locked into place between the tabs of two interlocking washers. As the name implies they are made of copper.